

# EasyLine XLP

## Общая информация

## Технические параметры

1-полюсный	XLP00			XLP1			XLP2			XLP3		
Номинальное рабочее напряжение, Ue AC [В]	-	500	690	-	500	690	-	500	690	-	500	690
Номинальное рабочее напряжение, Ue DC [В]	220	-	-	220	-	-	220	-	-	220	-	-
Номинальный рабочий ток, Ie [В]	160	160	125	250	250	200	400	400	315	630	630	500
Тепловой ток плавкой вставки, Ith [А]	160	160	160	250	250	250	400	400	-	630	630	-
Категория применения	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B
2-полюсный	XLP00			XLP1			XLP2			XLP3		
Номинальное рабочее напряжение, Ue AC [В]	-	500	690	-	500	690	-	500	690	-	500	690
Номинальное рабочее напряжение, Ue DC [В]	220	-	-	440	-	-	440	-	-	440	-	-
Номинальный рабочий ток, Ie [В]	160	160	125	250	250	200	400	400	315	630	630	500
Тепловой ток плавкой вставки, Ith [А]	160	160	160	250	250	250	400	400	-	630	630	-
Категория применения	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B	DC22B	AC22B	AC21B
4-полюсный	XLP00			XLP1			XLP2			XLP3		
Номинальное рабочее напряжение, Ue AC [В]		500			500			500			500	
Номинальный рабочий ток, Ie [В]		160			250			400			630	
Тепловой ток плавкой вставки, Ith [А]		160			250			400			630	
Категория применения		AC22B			AC22B			AC22B			AC22B	

## Информация для заказа

XLP 1-полюсный	
1SEP600113R0001	XLP00-1P
1SEP600113R0002	XLP00-1P-2BC
1SEP600113R0003	XLP00-1P-2M8
1SEP600116R0001	XLP1-1P
1SEP600116R0002	XLP1-1P-2BC
1SEP600116R0003	XLP1-1P-M10
1SEP600122R0001	XLP2-1P
1SEP600122R0002	XLP2-1P-2BC
1SEP600126R0001	XLP3-1P
1SEP600126R0002	XLP3-1P-2BC

XLP 2-полюсный	
1SEP600114R0001	XLP00-2P
1SEP600114R0002	XLP00-2P-4BC
1SEP600117R0001	XLP1-2P
1SEP600117R0002	XLP1-2P-4BC
1SEP600123R0001	XLP2-2P
1SEP600123R0002	XLP2-2P-4BC
1SEP600127R0001	XLP3-2P
1SEP600127R0002	XLP3-2P-4BC


XLP 3-полюсный	
1SEP201428R0001	XLP000-6CC
1SEP101890R0001	XLP00
1SEP101890R0002	XLP00-6BC
1SEP101890R0012	XLP00-EFM-6BC
1SEP101916R0001	XLP00-A60/60-B-3BC
1SEP101917R0001	XLP00-A60/60-A-3BC
1SEP101898R0002	XLP00-A40/75-B-3BC
1SEP101891R0002	XLP1-6BC
1SEP101891R0012	XLP1-EFM-6BC
1SEP101918R0001	XLP1-A60/85-B-3BC
1SEP101919R0001	XLP1-A60/85-A-3BC
1SEP101892R0002	XLP2-6BC
1SEP101892R0012	XLP2-EFM-6BC
1SEP101975R0001	XLP3
1SEP101975R0002	XLP3-6BC

XLP 4-полюсный	
1SEP600115R0001	XLP00-4P
1SEP600115R0002	XLP00-4P-8BC
1SEP600119R0001	XLP1-4P
1SEP600119R0002	XLP1-4P-8BC
1SEP600124R0001	XLP2-4P
1SEP600124R0002	XLP2-4P-8BC
1SEP600128R0001	XLP3-4P
1SEP600128R0002	XLP3-4P-8BC


# EasyLine XLP

## Габаритные размеры

### XLP00




### XLP1



# EasyLine XLP

## Габаритные размеры

### XLP2



### XLP3

